Infrared Thermometer Forehead



Technical Data

Accuracy	±0.2 degrees	Response time	0.5s
Abnormal automatic alarm	flashing +"Di Di" sound	Charging method	USB charging or battery.
Automatic measurement	measuring distance 5cm ~ 10cm	Input	USB DC 4.2-5V
Standby	About one week	Weight	350g
Install method	nail hook, double-sided adhesive sticking, bracket fixing	Dimensions	170*115*140mm
Operating temperature	10 C~40 C (Recommend 15 C~35 C)	Infrared measuring range	0~50 ℃
Standby	5s (Red dot dynamic cycle)	Screen	Digital display

